



# **Appliance Tester/Power Analyzer**

**Compact, battery operated device for analyzing AC power loads** With PC interface plus datalogging

## **Features:**

- Four simultaneous displays of Watts, Power Factor or VA, Voltage or Hz, Amps
- True RMS Voltage & Current measurements of sine, square, triangular and distorted wave forms with a crest factor < 5</li>
- Max, Data Hold and Overload Protection
- Battery or AC adaptor provides line isolation
- Plug device to be tested directly into the Power Analyzer
- Sampling (update) rate is 2.5 times/second
- Windows<sup>®</sup> 95/98/NT/2000/XP/ME software allows user to download stored data or save data directly, and to create an ASCII file. Computations include phase angle, apparent and reactive power, consumption and cost, and power factor correction
- Complete with Windows compatible software, cable, 8 x AA batteries, power cord, 117 VAC adaptor and case

## **Applications:**

- Measure and Audit power consumption of single phase devices
- Evaluate load performance under varying line conditions
- Demonstrate effectiveness of power conservation efforts
- Characterize device AC power requirements

### Model 380803 Datalogger

 Built-in Datalogger stores up to 1,012 readings (Single record storage or continuous datalogging)

#### Model 380801

Used for data acquisition when connected to a PC

**Ordering Information:** 





Optional Thermal Printer (PR20) prints text or graphics with fixed intervals or continuous



Software included to download and store data to a PC



Built-into heavy duty carrying case.

Specifications:	Range	Resolution	Basic Accuracy (%rdg)	Input Signal Range
Watt	200/2000W	0.1/1W	±(0.9% + 4d)@50/60Hz	300V, 20A, 40-400Hz
Power Factor	0.5 to 1.0	0.001	(Based on W, V, A)	250V, 20A, 50/60Hz
Voltage	200.0/750V	0.1/1V	±(0.5%)	750VAC
Current	2/20A via terminals		±(0.5%)	(Fuse Protection)
	2/15A via sockets			
Frequency	40Hz to 20kHz	1Hz to 10Hz	±(0.5%)	
Dimensions/Weight	13.9 x 11.8 x 3.9" (352 x 300 x 100mm) / 3.6 lbs. (1.6 kg)			



## www.extech.com